



IP Setup Instructions

For use with Marshall CV620-IP, CV355-30X-IP, and CV420-30X-IP cameras.

1. Marshall IP cameras are generally set to a FIXED IP address (or DHCP set to OFF) as default from Marshall factory and will be assigned the following fixed IP address of 192.168.100.100
2. First, set your computer to a fixed IP address of 192.168.100.99, done so to ensure that camera is not set to same fixed IP address as computer.
3. Open Internet Explorer (IE) and enter the camera's default IP address: 192.168.100.100

For use with DHCP, follow these instructions:

1. After doing the above steps, use IE to enter the cameras settings and change the camera to DHCP on the Network Tab and click Apply.
2. Change your computer to DHCP.
3. You will not know your camera's new IP address since it is set to DHCP and the IP address will automatically be assigned by your router network.



To find the camera's DHCP address, we recommend using **Onvif Device Manager**

Onvif Device Manager: <https://sourceforge.net/projects/onvifdm/>

Download the Onvif program from the link above and use it to discover the IP address of your camera. Note: ONVIF is not a Marshall Electronics product, but is widely used, and considered to be a safe download.

The connected camera model number should appear and be displayed when camera is found during the discovery function.

If you should have any questions or need additional help,
please call 800-800-6608 ext.1129